



## VOLTAGE DROP INSTRUCTIONS



Find the power to the wiper switch. It usually is on the last fuse (driver side) of the fuse box. There may be 3 wires on that terminal (1 red & black to the brake light switch, 1 black, blue & white to the flasher relay, and 1 black to the wiper switch.) After determining the best location for the “Voltage Drop”, cut the wire to the wiper switch and attach one end of the cut wire to one end of the “Voltage Drop”, attach the other end of the cut wire to the other end of the “Voltage Drop”. The “Voltage Drop” should be mounted somewhere safe and solid.

**CAUTION:** Resistors do get hot, therefore be sure that nothing contacts the “Voltage Drop”